



Product features:

- Power Factor Correction
- High Speed option as standard
- DMX control
- Modular Power Circuit

This ballast can operate up to 4 different lamp powers and works on worldwide mains supply voltages, making it a very flexible piece of kit to have available.

It has Power Factor Correction which minimises current draw and enables an 1800W lamp to be powered from a US 20A circuit.

This product is made using the Power Gems unique power module, which can be interchanged with modules from our 4kW or 6kW models.

PRODUCT SPECIFICATION			
Max Lamp Power	1800W	Output Power Options	1.8kW, 1.2kW, 800W, 575W
Output Frequency Options	1000Hz, 300Hz, 100Hz Silent Mode	Input Voltage Range	95-265V AC
Current Draw	8.7A @ 230V 16.7 A @ 120V	Power Factor	>0.98
DMX Built In	Yes	Max Ambient Temperature	45°C / 113°F
Width	225mm / 8.9"	Height	115mm / 4.5"
Length	350mm / 13.8"	Weight	7.5kg / 16.6lb

EB180P

1800W/1200W/800W/575W Electronic Ballast

