



# EB57P

## HIGH SPEED 575W/400W/200W BALLAST

### PRODUCT HIGHLIGHTS

THIS PRODUCT IS UNIQUE IN THE MARKET OFFERING 3 DIFFERENT OUTPUT SOCKETS TO DRIVE A MULTITUDE OF FIXTURES. TYPICALLY 7 DIFFERENT FIXTURE TYPES CAN BE DRIVEN FROM THIS ONE BALLAST MAKING IT THE IDEAL ACCOMPANIMENT FOR YOUR VALUABLE BUT LESS USED COLLECTION OF LOW POWER HEADS. OPERATES WITH FIXTURES FROM MOST MANUFACTURERS.

The EB57P is power factor corrected which minimises current draw thereby allowing you to make best use of the

available power when you don't have much capacity. Additionally, it ensures optimum ignition performance.

The ballast is based on Power Gems modular build technology for easy servicing and comes fully loaded with 1000Hz High

Speed operation, and DMX Control included as standard

### MAIN FEATURES

- 3 OUTPUT SOCKETS
- POWER FACTOR CORRECTION
- HIGH SPEED OPTION AS STANDARD
- DMX CONTROL
- MODULAR POWER CIRCUIT



### SPECIFICATIONS

Max Lamp Power	575W	DMX Built In	Yes
Output Power Options	575W, 400W, 200W	Max Ambient Temperature	45° / 113°F
Output Frequency Options	1000Hz, 300Hz, 100Hz, Silent Mode	Width	210mm/8.3"
Input Voltage Range	95-265V AC	Height	110mm/4.3"
Current Draw	2.6A @ 230V, 5.2A @ 120V	Length	250mm/9.8"
		Weight	3.9kg/8.6lb
		Power Factor	>0.98

### CONTACT

POWER GEMS LTD  
Unit 1, Fairhills Trade Centre,  
Fairhills Road,  
Irlam, Manchester M44 6BA.  
United Kingdom  
Tel +44 (0) 161 776 7030

POWER GEMS CORPORATION  
7702-1 Balboa Blvd., Van Nuys,  
California 91406. USA  
Tel +1 818 376 1800

[www.powergems.com](http://www.powergems.com)